

AR SERIES ARTISTE ORGANS

EARMARK FOR

#10650 FIRST PRESBYTERIAN CHURCH, MT. CLEMENS, MICHIGAN

SPECIFICATIONS OF TWELVE RANK ARTISTE ORGAN

PLUS TROMPETTE-EN-CHAMADE

GENERAL

(1) ORGAN

GREAT ORGAN
SWELL ORGAN
CHOIR ORGAN
TROMPETTE-EN-CHAMADE

SPECIAL, SEE
LAYOUT

Unenclosed and exposed
~~Standard Cabinet 1'-3" x 8'-0" x 8'-0" high~~
~~Standard Cabinet 1'-3" x 8'-0" x 8'-0" high~~
Unenclosed and exposed
Organ layout will be supplied. Swell and Choir organs and Great organ actions to be installed behind grilles to be supplied by customer. Fiberglass fabric by M. P. Moller, Inc. ^{SUBMITTED} Phillipine Mahogany to color block to be supplied
Electro-Pneumatic (unit type)
Great 3"; Swell and Choir Offsets 4-1/2",
Trebles 3-3/4" ~~Trompette En Chamade~~
A-440 @ 70° F

WOOD & FINISH
ACTION
WIND PRESSURE

PITCH

(2) CONSOLE

CABINET
WOOD & FINISH
MANUALS
MANUAL COMPASS
PEDAL COMPASS
STOP CONTROLS
ACTION

Special size and design
Phillipine Mahogany to color block ^{SUBMITTED} to be supplied
Three and Pedal
CC to Ch, 61 Notes
CCC to G, 32 Notes
Draw Knobs and Tilting Tablets
All Electric

(3) BLOWER

TYPE
RATING
CURRENT SPECIFICATION
OVERALL SIZE
BLOWER RESERVOIR
ENCLOSURE

MEIPINGER 140-8 - 2.5 HP - 1680
~~Kinetic Style 3-P-2724 - 1 1/2 HP - 1165 RPM~~
1450-1300 cfm @ 1/2" 10" outlet
3 Ph - 60 Cy - 220 Volts - 7.5 Amperes
2'-0" x 2'-0" x 3'-0" high
3'-0" x 2'-0" x 3'-0" 20/4
~~Special blower - reservoir - relay enclosure~~

(4) POWER UNIT (installed in Blower/Relay space)

TYPE
RATING
CURRENT SPECIFICATION
OVERALL SIZE

DC Organ Power Unit (all voltage)
DC Output: 10 to 15 Volts - 50 Amperes
AC Input: 1 Ph - 60 Cy - 220 Volts - 7 Amperes
1'-3-1/2" x 1'-11-1/2" x 10-1/2" high

CONSOLE AND ORGANGREAT ORGAN (*) (unenclosed and exposed)

1	8	Principal	85 Pipes
2	8	Bourdon	73 Pipes
3	4	Octavefrom #1.....	61 Notes
4	4	Bourdonfrom #2.....	61 Notes
5	2	Super Octavefrom #1.....	61 Notes
6	II	Mixture	122 Pipes
7		Chimespresent tubes, electric action, transformer and volume control. MPM to-supply new action relay only. A to F #22 to #42 incl...	21 Tubes

(*) Playable thru Relay and Switches by MPM, Inc.

SWELL ORGAN (*)

8	8	Rohrflöte	73 Pipes
9	8	Viola da Gamba	61 Pipes
10	4	Spitzprincipal	73 Pipes
11	4	Rohrflötefrom #8.....	61 Notes
12	2	Spitzoctavefrom #10.....	61 Notes
13	16	Contra Trompette	85 Pipes
14	8	Trompettefrom #13.....	61 Notes
15	4	Claironfrom #13.....	61 Notes
16		Tremolo	

(*) Playable thru Relay and Switches by MPM, Inc.

CHOIR ORGAN (*)

17	16	Lieblich Gedeckt	97 Pipes
18	8	Holzgedecktfrom #17.....	61 Notes
19	8	Dulciana TC	61 Pipes
20	4	Gedecktfrom #17.....	61 Notes
21	4	Dulcianafrom #19.....	61 Notes
22	2-2/3	Nazard	73 Pipes
23	2	Flautinofrom #17.....	61 Notes
24	1-1/3	Larigotfrom #22.....	61 Notes
25	8	Krummhorn	61 Pipes
26		Tremolo	
27	**8	Trompette - En -Chamade	61 Pipes

(**) Unenclosed and exposed

(*) Playable thru Relay and Switches by MPM, Inc.

PEDAL ORGAN (*)

28	16	Bourdon12 pipes; 20 from #2.....	32 Notes
29	16	Lieblich Gedecktfrom #17.....	32 Notes
30	8	Principalfrom #1.....	32 Notes
31	8	Bourdonfrom #2.....	32 Notes
32	8	Viola da Gambafrom #9.....	32 Notes
33	4	Octavefrom #1.....	32 Notes
34	4	Bourdonfrom #2.....	32 Notes
35	II	Mixturefrom #6.....	32 Notes
36	16	Contra Trompettefrom #13.....	32 Notes
37	8	Trompettefrom #13.....	32 Notes
38	4	Claironfrom #13.....	32 Notes

(*) Playable thru Relay and Switches by MPM, Inc.

COUPLERS

39	Great to Pedal
40	Swell to Pedal
41	Choir to Pedal
42	Swell to Great
43	Choir to Great
44	Swell to Choir

ADJUSTABLE COMBINATIONS

Pistons No. 1-2-3	Affecting Great Organ
Pistons No. 1-2-3	Affecting Swell Organ
Pistons No. 1-2-3	Affecting Choir Organ
Toe Studs No. 1-2-3	Affecting Pedal Organ
Pistons No. 1-2-3-4-5-6	Affecting Full Organ (duplicated by toe studs)
General Cancel	

PEDAL MOVEMENTS

- 1- Great to Pedal Reversible (toe stud only)
- 2- Balanced Expression Pedal - Swell Organ (8 stages)
- 3- Balanced Expression Pedal - Choir Organ (8 stages)
- 4- Balanced Crescendo Pedal with indicator light (green jewel)
- 5- Sforzando Reversible (toe stud only) with indicator light (red jewel)

ACCESSORIES

Motor and power unit on-off switch (lock type) with indicator light (red jewel) and related electrical wiring.

Flexiglas music rack with fluorescent light.
Pedal light (to come on with motor)

Concave and radiating pedal keyboard.
Organ bench with music shelf.

Supply flexaust to enclose cables between console and organ.

ELECTRIC CLOCK