

AR SERIES ORGANS

EARMARK FOR

#11453 HOLY ANGEL'S CHURCH, BARRINGTON, RHODE ISLAND
SPECIFICATIONS OF A 6 RANK SERIES 70 ORGAN

26

GENERAL

ORGAN

Cabinet	Standard design with exposed 8 Principal
	Layout will be supplied
Wood & Finish	Rift Sawn Oak - M-4150-2
Action	Electro-Pneumatic
Wind Pressure	See Pipe Analysis
Pitch	A-440 @ 70°F

CONSOLE

Cabinet	Standard design with roll top
Wood & Finish	Rift Sawn Oak - M-4150-2
Manual	Two and Pedal
Manual Compass	CC to C4, 61 notes
Pedal Compass	CCC to G, 32 notes
Stop Controls	Tilting Tablets
Action	All Electric

BLOWER (located in blower space)

Type	Meidinger 1002 - .4 HP - 3360 RPM - 4" outlet
Wind	300 C.F.M. @ 4"
Current Specifications	1 Ph - 60 Cy - 120 Volts - 4.4 Amperes
Overall Size	1' - 6-7/8" x 1' - 6-1/8" x 1' - 10-1/4" high

POWER UNIT (located in blower space)

Rating	DC Output: 10-15 Volts - 30 Amperes
Current Specification	AC Input: 1 Ph - 60 Cy - 120 Volts - 10 Amperes
Overall Size	14-1/2" long x 10-3/4" x 7" high

GREAT ORGAN (Enclosed)

16	Bourdon-----	92 pipes
8	Principal -----	85 pipes
8	Gedeckt -----from #1-----	61 notes
8	Gemshorn -----	80 pipes
4	Octav -----from #2 -----	61 notes
4	Gedeckt -----from #1 -----	61 notes
2	Super Octav -----from #2 -----	61 notes
2	Flute -----from #1--(repeat 5 top notes)-----	61 notes
8	Trompette-----from #18 -----	61 notes
	Chimes-----Mayland tubes and electric actions, relay, transformer and volume control - A to F - #22 to #42-----	21 tubes

(*) Exposed

SWELL ORGAN

11	8	Gedeckt-----from #1-----61 notes
12	8	Gemshorn-----from #4-----61 notes
13	8	Gemshorn Celeste TC-----49 pipes
14	4	Spitzprincipal-----73 pipes
15	4	Gedeckt -----from #1-----61 notes
16	2	Spitzoctav -----from #13-----61 notes
17	1-1/3	Larigot -----from #4--(repeat 12 top notes)-----61 notes
18	8	Trompette -----61 pipes
19	4	Clairon -----from #18--(top Octave from #14) -----61 notes
20		Tremolo

PEDAL ORGAN

21	16	Bourdon-----from #1 -----32 notes
22	8	Principal -----from #2 -----32 notes
23	8	Gedeckt-----from #1 -----32 notes
24	8	Gemshorn -----from #4 -----32 notes
25	4	Octav -----from #2 -----32 notes
26	4	Gedeckt-----from #1 -----32 notes
27	2	Super Octav -----from #2 -----32 notes
28	8	Trompette -----from #18 -----32 notes
29	4	Clairon -----from #18 -----32 notes

COUPLER

30 Swell to Great

ADJUSTABLE COMBINATIONS

Pistons No. 1-2-3-4

Affecting Full Organ

PEDAL MOVEMENTS

- 1 - Balanced Expression Pedal (8 contacts, reverse system)
- 2 - Balanced Crescendo Pedal with indicator light (green jewel)

ACCESSORIES

Motor and power unit On-Off switch (toggle type) with indicator light (amber jewel)
and related electrical wiring.
Concave and radiating pedal keyboard
Organ bench with music shelf
Music rack
Music rack light
Pedal light

PIPE ANALYSIS

STOP	PITCH	PIPES	SCALE	HALVING	MOUTH	METAL	WIND PRESSURE
Bourdon	16	92	CCC to BBB Regular Manual Bourdon CC to BB Reg. Artiste Tapered Bass TC 68	21-1/2	2/9	Wood) Wood) 5 Zinc C.M.)	3-1/2"
*Principal	8	85	48	18-1/2	1/4	19 Zinc S.M.	3-1/2"
Gemshorn	8	80	CC 56 C 68-1/2 #56 98	19-1/2 19-1/2 17-1/2	2/9 2/9 1/6	) 17 Zinc S.M.))	3-1/2"
Gemshorn Celeste	8 TC	49	56-1/2 @ 8' CC	19-1/2	2/9	5 Zinc S.M.	3-1/2"
Spitzprincipal	4	73	60-2/3	18-1/2	1/4	7 Zinc C.M.	3-1/2"
Trompette	8	61	2-1/4" CC to FF half length FF# up full length			D(F) Eschallots Zinc & S.M.	3-1/2"

(*) Exposed