

M. P. MÖLLER Organ Factory

Pipe Organ No. 7404 Date June 21, 1946
 For CANTON METHODIST CHURCH, BALTIMORE, MARYLAND
 Action Electro-pneumatic Console Detached
 Casing No. None Finish As per Sample
 Decorations None Motor 3/4 H.P., Style 3-P-2421
 Width of Key-bed Standard Stop Controls Stop Keys
 No. Manuals TWO Wind Pressure 4 1/2"
 To be Completed As soon as possible. Blower Pipe furnished by Purchaser

PITCH: A-440
 All Units

SPECIFICATIONS

GREAT ORGAN

1	8'	Diapason.....44 sc.....	20 Zinc C.M.....	73 Pipes
2	8'	Gedeckt.....L.M.B. Bass....	Reg. Stopped Flute Treble.....	85 Pipes
3	8'	Viole Dolce.....58 sc.....	20 Zinc S.M.....	85 Pipes
4	4'	Octave.....	from #1.....	61 Notes
5	4'	Flute.....	from #2.....	61 Notes
6	4'	Fugara.....	from #3.....	61 Notes
7	2-2/3'	Viole Twelfth.....	from #3.....	61 Notes
8	2'	Viole Fifteenth.....	from #3.....	61 Notes
9	8'	Trumpet.....	from #17.....	61 Notes

9a

Chimes (Prepared for in console only) Organ "D" A to G

SWELL ORGAN

22 to 42 21 to

10	16'	Bourdon...T.C.....	from #2.....	49 Notes
11	8'	Gedeckt.....	from #2.....	61 Notes
12	8'	Viole Dolce.....	from #3.....	61 Notes
13	4'	Flute.....	from #2.....	61 Notes
14	4'	Fugara.....	from #3.....	61 Notes
15	2-2/3'	Flute Twelfth.....	from #2.....	61 Notes
16	2'	Flautino.....	from #2.....	61 Notes
17	8'	Trumpet.....4"		73 Pipes
18	4'	Clarion.....	from #17.....	61 Notes
19		Tremulant		

PEDAL ORGAN

20	16'	Bourdon.....#2 Ped. Bdn.....	12 pipes.....20 from #2.....	32 Notes
21	8'	Diapason.....	from #1.....	32 Notes
22	8'	Flute.....	from #2.....	32 Notes
23	4'	Octave.....	from #1.....	32 Notes
24	4'	Flute.....	from #2.....	32 Notes

COUPLERS

25	Swell to Great
26	Great to Pedal
27	Swell to Pedal

Organ Built by M. P. Möller Inc.

ADJUSTABLE COMBINATIONS

(Operated by pistons placed under Great Manual)

Pistons No. 1-2-3-4

Affecting Full Organ

PEDAL MOVEMENTS

Great to Pedal Reversible
Balanced Expression Pedal
Balanced Crescendo Pedal

ACCESSORIES

Crescendo Indicator (lights)
Concave, Radiating Pedal Clavier
Organ Bench with Music Shelf
Electric motor, blower and action current generator of ample capacity.

*Motor Starter switch to be supplied and installed at right
of manual keys*

JHH/br
7/18/46