M. P. MÖLLER Organ Factory

	M. P. MOLLER	Organ Factory				
	3/24	Rev. February 16, 1972				
Pipe Organ No	R-653	Date July 23, 1971	District Cartes Carverse			
For	ST. JOHN'S CATHOLIC CHURCH,	WESTMINSTER, MARYLAND	ESSESSES CARROLLA			
Action	Electro-Pneumatic	Console Detached	Resignation come as			
Casing No	None	Finish No Change	RE-POSICIONE			
Decorations	None	Motor Present blower with new	notor			
Width of Key-bed.	Standard	Stop Controls No Change	ting with the state of			
No. Manuala	THREE AND PEDAL	Wind Pressure No Change	PARTINGENERAL APPLO			
To be Completed	December 20, 1971	Blower Pipe furnished by Purchase	Z maneumaniana			
	SPECIFICA'	CIONS				
	FOR	2000				
R	BBUILDING PRESENT M. P. MCLL Rebuild R-449 - 1					
CONSCLE	Rebuild present three manua and organ bench as follows:	l stop key console, pedal keyboard	COMP			
	and organ pench as lorrows:					
	Recover 26 coupler pneumatics					
	Recover combination pne Releather Great to Peda					
	Releather Sforzando mechanism					
	Releather 30 note primary					
	Refelt console completely Regulate and adjust action					
		nd install new tips on wiper wires	3 0			
MANUAL CHESTS	MANNIAL CHESTS Releather 1218 manual pipe pouches.					
	Install 1827 new stop action checks and eyelets.					
	Install 609 new duplex shifters. Releather 28 stop action primaries.					
	Releather four 73 note primary stations.					
	Install 320 new magnet plugs and armatures.					
UNIT AND			3			
OFFSET ACTIONS	Releather the following and	install new magnet plugs and arms	atures:			
	Great 16 Open Diapason	action - 18 notes				
	Great 8 First Open Dia	pason action - 12 notes				
	Great 8 Second Open Di Great 8 Geashorn - 4 :	apason action - 12 notes				
	Great III Mixture - 61					
	Swell 16 Bourdon - 97					
	Swell 8 Open Diapason					
	Swell & Vox Humana - (Choir & Clarinet - 61					
		ntact Box and install new silver w	iro			
CONTACT BOXES	contact blocks.	ital a service in the service of the				
		or contact boxes as follows:				
	16 Open Diapason #1 to	#12 incl.				
	16 Open Diapason #13 to					

8 First Open Diapason #1 to #12 incl. 8 Second Open Diapason #1 to #12 incl.

8 Gemshorn #1 to #4 incl.

2-853

SWITCHES

Install the following new electro-pneumatic switches with stop actions:

Great Station "A" cutout - 73 notes

Great Station "B" cutout - 73 notes

Great III Mixture - 61 notes

Great Chimes - 25 notes

Swell Station cutout - 73 notes

Swell 16 Bourdon - 73 notes

Swell 8 Open Diapason - 10 notes

Swell 8 Stopped Diapason - 73 notes

Swell 4 Orchestral Flute - 73 notes

Swell 2-2/3 Flute Twelfth - 61 notes

Swell 2 Fifteenth - 61 notes

Swell 1 Fife - 61 notes

Swell 8 Vox Humana - 61 notes

Choir Station cutout - 73 notes

Choir 8 Clarinet - 61 notes

Choir Harp - 49 notes

CHIMES

Releather and refelt 21 note Chimes action and install new magnet plugs and armatures.

Recover 21 chime pneumatics.

HARP

Releather and refelt 49 note Harp action and install new magnet plugs and armatures.

Recover 49 Harp pneumatics.

PBDAL ORGAN

Releather 16 First Open Diapason action #1 to #44 incl. and install new magnet plugs and armatures.

Releather 16 Bourdon action #1 to #44 incl. and install new magnet plugs and armatures.

Releather 14 note 16 Second Open Diapason primary and install new magnet plugs and armatures.

Releather 32 note 8 Tuba Primary and install new magnet plugs and armatures.

Install new 32 note Pedal Relay with seven 32 note switches.

EXPRESSION

Releather 12 note expression action for Great-Choir organ. Releather 10 note expression action for Swell Organ.

Recover 22 Shade and bumper pneumatics.

Install additional shades and action as required.

Install additional swell box as required

RESERVOIRS

Recover the following reservoirs and install new curtain valves as required:

Three (3) 2'-6" x 4'-0" Manual Reservoirs

Four (4) Pedal and Offset Reservoirs

Two (2) Shade Reservoirs

One (1) Chines and Harp Reservoir

One (1) Console Reservoir

PAGE 3

ST. JOHN'S CATHOLIC CHURCH, WESTMINSTER, MARYLAND

TREMOLO

R-853

Install three new electro-pneumatic tremolos.

PIPES

Repack stoppers of existing wood pipes.

CABLES

Install new plastic covered cables between console and organ.

Install new action current wires between console, organ and power unit.

BLOWER

Install new 5 H.P. motor on existing blower.

POWER UNIT

Install new organ power unit of ample capacity.

GENERAL

Entire organ with exception of organ case and display pipes to be returned to the factory of M. P. Moller, Inc., at Hagerstown, Md. for releathering, re-engineering, rebuilding and re-installation in new church building in accordance with specifications listed below.

SPECIFICATIONS FOR CONSOLE AND ORGAN

MANUAL COMPASS PEDAL COMPASS WIND PRESSURE PITCH

IA

CC to C4, 61 notes CCC to G, 32 notes 6" A-440 @ 70°F

Tremolo

GREAT ORGAN 13

1	16	Open Diapasonpresent pipes; present action85 p	pipes
2	3	First Open Diapasonpresent pipes; present action61 p	
3	8	Second Open Diapason.present pipes; present action73 p	pipes
4	8	Doppel Flute present pipes; present action 73 p	pipes
5	8	Concert Flutepresent pipes; present action73 p	pipes
6	8	Violapresent pipes; present action73 p	pipes
7	8	Genshorn present pipes; present action 73 p	pipes
8	4	Octave	ootes
9	4	Flute Harmoniquepresent pipes; present action73 p	pipes
10	2	Piccolo	pipes
11	III	Mixture present pipes; present action 183 p	pipes
12	8	Tuba	pipes
13		Chimes	
		A to F, #22 to #42 incl	tubes

	•					
R-853		ST. JOHN'S CATHOLIC CHURCH, WESTMINSTER, MARYLAND PAGE 4				
SWELL ORGAN 7						
15	16	Bourdon (unit) present pipes; present action 97 pipes				
16	8	Open Diapasonpresent pipes; present action73 pipes				
17	8	Stopped Diapasonfrom #15				
18	8	Salicionalpresent pipes; present action73 pipes				
19	8	Vox Celeste T.Cpresent pipes; present action ol pipes				
20	A	Orchestral Flutefrom #15				
21	4	Salicet				
22	2-2/3	Flute Twelfth				
23	2	Fifteenth				
24	1	Fife				
25	8	French Trumpetpresent pipes; present action				
26	8	Choe				
27	8	Vox Humana present pipes; present action 61 pipes				
28		Tremolo				
**	CHOIR ORGAN 2					
29	8	English Open Diapason . from #1 , , , , , , , , , , , , , , , 73 motes				
30	8	Concert Flute from #5 73 notes				
31	8	Dulciana present pipes; present action 73 pipes				
32	8	Genshorn from #7 con consequence 73 notes				
33	8	Viola from #6 73 notes				
34	4	Dulcet 61 notes				
35	4	Flute from #9				
36	2	Piccolo				
37	8	Clarizet present pipes; present action 61 pipes				
38	4	Harp present resonators; present action wired #13 to #61 incl				
39		Trenclo				
	4					
	is	PEDAL ORGAN (*) 2				
40	16	First Open Diapason present pipes; present action 44 pipes				
41	16	Second Open Diapason from #1 32 notes				
42	16	Bourdon present pipes; present action 44 pipes				
43	16	Lieblich Gedecktfrom #15				
44	8	Octave				
45	8	Flute Stom #42 con conconce con conconce 32 notes				
46	8					

(*) Pedal Organ playable thru new Pedal Relay and Switches.

COUPLERS

47	Great to Pedal	61	Choir	to Swell 16
48	Great to Pedal 4	62	Choir	to Swell
49	Swell to Pedal	63	Choir	to Swell 4
50	Swell to Pedal 4	64	Swell.	16
51	Choir to Pedal	65	Swell	Unison Off
52	Swell to Great 16	66	Swell	4
53	Swell to Great	67	Swell	to Choir 16
54	Swell to Great 4	68	Swell	to Choir
55	Choir to Great 16	69	Swell	to Choir 4
56	Choir to Great	70	Choir	16
57	Choir to Great 4	71	Choir	Unison Off
58	Great 16	72	Choir	4
59	Great Unison Off			
60	Grant A			

ADJUSTABLE COMBINATIONS

Pistons	No.	1-2-3-4-5-6	Affecting	Great	Stops
Pistons	No.	1-2-3-4-5-6	Affecting	Swell	Stops
Pistons	No.	1-2-3-4-5-6	Affecting	Choir	Stops
Pistons	No.	1-2-3-4-5-6	Affecting	Pedal	Stops
Pistons	No.	1-2-3-4-5-6	Affecting	Full	Organ

PEDAL MOVEMENTS

- 1 Great to Pedal Reversible
- 2 Balanced Expression Pedal for Great-Choir Organ (18 contacts, regular system)
- 3 Balanced Expression Pedal for Swell Organ (14 contacts, regular system)
- 4 Balanced Crescendo Pedal with indicator light (green jewel)
- 5 Sforzando Reversible

ACCESSORIES

Present concave and radiating pedal keyboard Present organ bench with masic shelf Present blower with 5 H.P. motor New organ power unit of ample capacity

8/11/71 RHM/mr Revised 2/16/72