

Mr. Daniels M-1703

CONSOLE SPECIFICATIONS

PROD. ORDER #M-1703

June 9, 1966

B. L. MCCRARY, OKLAHOMA CITY, OKLAHOMA

FOR

HAHN-COOK FUNERAL HOME, OKLAHOMA CITY, OKLAHOMA

CONSOLE
CABINET DESIGN
WOOD
FINISH
MANUALS
MANUAL COMPASS
PEDAL COMPASS
STOP CONTROLS
ACTION
ACTION CURRENT SUPPLY

Detached
Style A4 *with roll top & lock*
~~To customer's selection~~ *Rift Sawn Oak*
To color block ~~to be~~ submitted
Two and Pedal
CC to C4, 61 Notes
CCC to G, 32 Notes
Tilting Tablets
All Electric
15 Volts DC

GREAT ORGAN (73 note station)

- 1 8 Open Diapason
- 2 8 Dulciana
- 3 8 Flauto Dolce
- 4 8 Clarinet
- 5 Blank Tilting Tablet
- 6 Chimes.....provide switch in console wired
G to G #20 to #44 incl.....25 Notes
- 7 Tremolo

SWELL ORGAN (73 note station)

- 8 8 Stopped Diapason
- 9 8 Aeoline
- 10 4 Flute D'Amour
- 11 8 Vox Humana
- 12 Blank Tilting Tablet
- 13 Blank Tilting Tablet
- 14 Harp
- 15 Tremolo

PEDAL ORGAN (*)

- 16 16 Bourdon.....56 Pipes
- 17 8 Flute.....from #16.....32 Notes
- 18 4 Bourdon.....from #16.....32 Notes
- 19 Blank Tilting Tablet. *(wire to 32 note junction)*
- 20 Chimes.....from #6.....25 Notes

(*) Pedal Organ playable thru slides in console

COUPLERS

21	Great to Pedal	28	Great 16
22	Great to Pedal 4	29	Great Unison Off
23	Swell to Pedal	30	Great 4
24	Swell to Pedal 4	31	Swell 16
25	Swell to Great 16	32	Swell Unison Off
26	Swell to Great	33	Swell 4
27	Swell to Great 4		

ADJUSTABLE COMBINATIONS

Pistons No. 1-2-3-4	Affecting Great & Pedal Stops
Pistons No. 1-2-3-4	Affecting Swell & Pedal Stops
General Cancel Piston	

PEDAL MOVEMENTS

- 1- Great to Pedal Reversible
- 2- Swell to Pedal Reversible
- 3- Balanced Expression Pedal for Swell Organ with indicator light (white jewel)
(12 contacts, regular system)
- 4- Balanced Crescendo Pedal with indicator light (green jewel)

ACCESSORIES

- Action current indicator light (white jewel)
- Concave and radiating pedal keyboard
- Organ bench with music shelf