

Mr. Daniels

CONSOLE SPECIFICATIONS

PROD. ORDER #M-1174

Sept. 17, 1965

FIRST CONGREGATIONAL CHURCH, HUDSON, OHIO

CONSOLE	Detached
CABINET DESIGN	with roll top
WOOD	Walnut
FINISH	To M. P. M. color block #M-622
MANUALS	Three and Pedal
MANUAL COMPASS	CC to C ₄ , 61 Notes
PEDAL COMPASS	CCC to G, 32 Notes
STOP CONTROLS	Draw Knobs & Tilting Tablets
ACTION	Electro-Pneumatic
WIND PRESSURE	
ACTION CURRENT SUPPLY	New 30 Ampere Orgelectra

GREAT ORGAN

1	8	Principal
2	8	Gedeckt
3	4	Spitz Octave
4	2-2/3	Nazard
5	8	Trompette
6		Chimes

SWELL ORGAN

7	16	Bourdon
8	8	Holzgedeckt
9	8	Viole de Gambe
10	8	Viole Celeste
11	4	Prestant
12	2-2/3	Nazard
13	2	Cor de Nuit
14	8	Trompette
15		Blank Draw Knob
16		Tremolo

CHOIR ORGAN

17	8	Gedeckt
18	8	Dulciana
19	4	Spillflote
20	8	Clarinet
21		Blank Draw Knob
22		Tremolo

PEDAL ORGAN (*)

23	16	Contrabass.....	44 Pipes
24	16	Bourdon.....from #7.....	32 Notes
25	8	Octave.....from #23.....	32 Notes
26	8	Bourdon.....from #7.....	32 Notes
27		Blank Draw Knob	

(*) Pedal Organ playable thru new Pedal Relay and switches to be supplied by M. P. Moller, Inc.

COUPLERS

28	Great to Pedal	40	Great 4
29	Great to Pedal 4	41	Swell 16
30	Swell to Pedal	42	Swell Unison Off
31	Swell to Pedal 4	43	Swell 4
32	Choir to Pedal	44	Swell to Choir 16
33	Choir to Pedal 4	45	Swell to Choir
34	Swell to Great 16	46	Swell to Choir 4
35	Swell to Great	47	Choir 16
36	Swell to Great 4	48	Choir Unison Off
37	Choir to Great 16	49	Choir 4
38	Choir to Great		
39	Choir to Great 4		

ADJUSTABLE COMBINATIONS

Pistons No. 1-2-3	Affecting Great Stops
Pistons No. 1-2-3-4	Affecting Swell Stops
Pistons No. 1-2-3	Affecting Choir Stops
Toe Studs No. 1-2-3	Affecting Pedal Stops
Pistons No. 1-2-3-4-5-6	Affecting Full Organ (duplicated by toe studs)
General Cancel Piston	

PEDAL MOVEMENTS

- 1- Great to Pedal Reversible (duplicated by manual piston)
- 2- Swell to Pedal Reversible (duplicated by manual piston)
- 3- Choir to Pedal Reversible (duplicated by manual piston)
- 4- Balanced Expression Pedal - Swell Organ (16 contacts, regular system)
- 5- Balanced Expression Pedal - Choir Organ (16 contacts, regular system)
- 6- Balanced Crescendo Pedal with indicator light (green jewel)
- 7- Sforzando Reversible (duplicated by manual piston) with indicator light (red jewel)

ACCESSORIES

Signal light(white jewel) with marker engraved: Narthex
 Music rack light
 Pedal light
 Motor starter switch mounted in console
 Concave and radiating pedal keyboard
 Organ bench with music shelf
 New 30 Ampere 1 Phase 110 Volt Orgelectra Organ Power Unit