

AR SERIES ORGAN
 EARMARK FOR
 #11152 FIRST UNITED METHODIST CHURCH, BRISTOW, OKLAHOMA
 SPECIFICATIONS FOR A SERIES 70-6 ORGAN

2/3

GENERAL

(1) ORGAN

Great Organ	Standard design without grille
Swell Organ	Standard design without grille
	Layout will be supplied
Wood & Finish	Silvite, Dull Charcoal Brown
Action	Electro-Pneumatic (unit type)
Wind Pressure	See Pipe Analysis
Pitch	A-440 @ 70°F

(2) CONSOLE

Cabinet	Standard Design
Wood & Finish	Rift Sawn Oak - #4159-2 <i>to customer's sample</i>
Manual	Two and Pedal
Manual Compass	CC to C4, 61 notes
Pedal Compass	CCC to G, 32 notes
Stop Controls	Tilting Tablets
Action	All Electric

(3) BLOWER (located below organ platform)

Type	Kinetic 2-P-2116 - 1/2 H.P. - 1750 RPM
Rating	500 c.f.m. @ 4" - 6" outlet
Current Specifications	1 Ph - 60 Cy - 240 Volts - 3.6 Amperes
Overall Size	2'- 5-3/4" long x 1' - 10-3/8" wide x 2' - 6-1/4" high

(4) POWER UNIT (located in console cabinet)

Rating	DC Output - 10-15 Volts - 30 Amperes
Current Specifications	AC Input 1 Ph - 60 Cy - 120 Volts - 10 Amperes
Overall Size	14-1/2" long x 10-3/4" wide x 7" high

* * * * *

CONSOLE AND ORGAN

GREAT ORGAN (Enclosed)

1	16	Bourdon	92 pipes
2	8	Principal.....	80 pipes
3	8	Gedeckt.....from #1.....	61 notes
4	8	Gemshorn.....from #13.....	61 notes
5	4	Octave	61 notes
6	4	Gedeckt	61 notes
7	2	Super Octave.....from #2..(repeats 5 top notes).....	61 notes
8	2	Flute	61 notes
9	II-III	Mixture.....	126 pipes
10		Chimes.....(prepared for in console only)	
11		Tremolo	

SWELL ORGAN (Enclosed)

12	8	Spitzflöte.....(low octave from #13).....	68 pipes
13	8	Gemshorn	85 pipes
14	4	Spitzflöte.....from #12.....	61 notes
15	2	Spitzflöte.....from #12..(repeat 5 top notes).....	61 notes
16	1-1/3	Larigot.....from #13..(repeat 7 top notes).....	61 notes
17	16	Contre Trompette	80 pipes
18	8	Trompette.....from #17	61 notes
19	4	Clavier <i>Clavier</i>from #17..(repeat 5 top notes).....	61 notes
20		Tremolo	

PEDAL ORGAN

21	16	Bourdon.....from #1.....	32 notes
22	8	Principal	from #2.....32 notes
23	8	Gedeckt	from #1.....32 notes
24	8	Gemshorn	from #13
25	4	Octave.....	from #2.....32 notes
26	4	Spitzflöte.....	from #12
27	III	Mixture	from #7 & 9
28	16	Contre Trompette	from #17
29	8	Trompette	from #17.....32 notes
30	4	Clavier <i>Clavier</i>	from #17

COUPLER

31 Swell to Great

ADJUSTABLE COMBINATIONS

Pistons No. 1-2-3-4

Affecting Full Organ

PEDAL MOVEMENTS

Balanced Expression Pedal - Great Organ (8 contacts, reverse system)
 Balanced Expression Pedal - Swell Organ (8 contacts, reverse system)
 Balanced Crescendo Pedal with indicator light (green jewel)

ACCESSORIES

Motor and power unit on-off switch (lock type) with indicator light (red jewel)
 and related wiring.
 Concave and radiating pedal keyboard
 Organ bench with music shelf
 Music rack

PIPE ANALYSIS

STOP	PITCH	PIPES	SCALE	HALVING	MOUTH	METAL	WIND PRESSURE
<u>GREAT ORGAN</u>							
Bourdon	16	92	CCC to BBB Reg. Manual Bourdon			Wood	) 1-16 4-1/2"
			CC to BB Reg. Artiste Tapered Bass			Wood	) 17 up 3-1/2"
			TC up Reg. Artiste Treble			Wood & S.M.)	
Principal	8	80	CC 52 TC 60	18-1/2	1/4	17 Zinc S.M.)	1-12 4-1/2" 13 up 3-1/2"
Mixture	II-III	126	See Formula Below				3-1/2"

SWELL ORGAN

Spitzflote T.C.	8	68	60-2/3 @ 4' C	19-1/2	1/5	5 Zinc S.M.	3-1/2"
Gemshorn	8	85	CC 54	17-1/2			
			C 66-1/3	17-1/2	2/9	17 Zinc S.M.	3-1/2"
			#56 102-2/3	18-1/2			
Contre Trompette	16	80	2-1/2" CCC to FF half length FF# up full length D(F) Eschallots			Zinc & S.M.	3-1/2"

* * * * *

GREAT II-III MIXTURE FORMULA

	19	12	12	12	15
	22	19	19		
		22			
	1-37	38-49	50-53	54-56	57-61
Unison	47 Sc.	17-1/2	1/4 mouth	S.M.	
Quint	49 Sc.	17-1/2	1/4 mouth	S.M.	