

File

CONSOLE SPECIFICATIONS

PROD. ORDER M-1188

January 25, 1979

WESTMINSTER PRESBYTERIAN CHURCH
SACRAMENTO, CALIFORNIA

CONSOLE
CONSOLE DESIGN
CABINET WOOD
CABINET FINISH
MANUALS
MANUAL COMPASS
PEDAL COMPASS
STOP CONTROLS
ACTION
WIND PRESSURE
ACTION CURRENT SUPPLY

Detached - No roll top
Style A-6
Rift Saw wood
To customer's sample
Four and Pedal
CC to C4, 61 notes
CCC to G, 32 notes
Draw Knobs & Tilting Tablets
Electro-Pneumatic
5-1/2" to 6"
12 Volts DC

GREAT ORGAN - 61 note compass

1	8	Open Diapason
2	8	Doppel Flute
3	8	Viole De Gambe
4	8	Clarabella
5	4	Erzahler
6	4	Harmonic Flute
7	8	Trumpet
8		Blank
9		Major Bells - not affected by couplers, provide switch wired to junction board - - - - - 61 notes

SWELL ORGAN - 61 note compass

10	16	Bourdon
11	8	Diapason
12	8	Gedeckt
13	8	Quintadena
14	8	Viole D'Orchestre
15	8	Salicional
16	8	Voix Celeste
17	8	Aeoline
18	4	Flauto Dolce
19	2-2/3	Nazard
20	2	Piccolo
21	8	Cornocean
22	8	Oboe
23		Blank
24		Tremolo
25		Symphonic Carillon - not affected by couplers, provide switch wired to junction ----- 61 notes

CHOIR ORGAN - 61 note compass

26	8	Violin Diapason
27	8	Concert Flute
28	8	Dulciana
29	8	Unda Maris
30	4	Flute D'Amour
31	8	English Horn
32		Blank
33		Blank
34		Blank
35		Blank
36		Tremolo

POSITIV ORGAN - 61 note compass

37	8	Nason Flute
38	4	Koppel Flute
39	2-2/3	Nasat
40	2	Italian Principal
41	1-3/5	Terz
42	1	Siffelöte
43	8	Krummhorn
44		Tremolo

GALLERY ORGAN - 61 note compass

45	8	Viola Etheria
46	8	Wald Flute
47	8	Clarinet
48		Blank
49		Blank
50		Blank
51		Blank
52		Blank
53		Tremolo

* PEDAL ORGAN

54	32	Resultant Bass	switch wired to junction - - - - - 32 notes
55	16	Diapason	switch wired to junction - - - - - 32 notes
56	16	Bourdon	switch wired to junction - - - - - 32 notes
57	16	Violone	switch wired to junction - - - - - 32 notes
58	16	Lieblich Gedeckt	switch wired to junction - - - - - 32 notes
59	8	Cello	switch wired to junction - - - - - 32 notes
60	8	Flauto Dolce	switch wired to junction - - - - - 32 notes
61		Blank	
62		Blank	
63		Blank	
64		Blank	
65		Blank	
66		Blank	
67		Blank	
68		Blank	
69		Blank	
70		Blank	

* PEDAL ORGAN (continued)

71 Blank
 72 Blank
 73 Blank
 74 Blank
 75 *Blank* ~~Bells~~ (Prep for Bells) switch wired to junction - - - - - 32 notes

* Provide unison wired to junction for future relay to play #61 thru 74.

COUPLERS

76	Great to Pedal	93	Swell to Choir - Positiv 16
77	Great to Pedal 4	94	Swell to Choir - Positiv
78	Swell to Pedal	95	Swell to Choir - Positiv 4
79	Swell to Pedal 4	96	Gallery to Choir-Positiv
80	Choir-Positiv to Pedal	97	Great 16
81	Choir-Positiv to Pedal 4	98	Great Unison Off
82	Gallery to Pedal	99	Great 4
83	Swell to Great 16	100	Swell 16
84	Swell to Great	101	Swell Unison Off
85	Swell to Great 4	102	Swell 4
86	Choir-Positiv to Great 16	103	Choir-Positiv 16
87	Choir-Positiv to Great	104	Choir-Positiv Unison
88	Choir-Positiv to Great 4	105	Choir-Positiv off 4
89	Gallery to Great 16	106	Gallery 16
90	Gallery to Great	107	Gallery Unison Off
91	Gallery to Great 4	108	Gallery 4
92	Gallery to Swell 8		

ADJUSTABLE COMBINATIONS

Pistons No. 1-2-3-4-5-6	Affecting Great
Pistons No. 1-2-3-4-5-6	Affecting Swell
Pistons No. 1-2-3-4-5-6-7-8	Affecting Choir-Positiv
Pistons No. 1-2-3-4	Affecting Gallery
Toe Studs No. 1-2-3-4-5-6	Affecting Pedal
Pistons No. 1-2-3-4-5-6-7-8	Affecting Full Organ
General Cancel	

REVERSIBLES

Great to Pedal - manual piston and toe stud
 Swell to Pedal - manual piston and toe stud
 Choir-Positiv to Pedal - manual piston and toe stud
 Gallery to Pedal - manual piston and toe stud
 Sforzando - toe stud with indicator light (red jewel)
 All Swells to Swell - toe stud

PEDAL MOVEMENTS

Balanced Expression Pedal - Swell Organ (16 contacts, *make to close* ~~system~~)
Balanced Expression Pedal - Choir Organ (8 contacts, *make to open* ~~system~~)
Balanced Expression Pedal - Gallery Organ (8 contacts, *make to open* ~~system~~)
Balanced Crescendo Pedal - with 6 indicator lights (green jewels)

ACCESSORIES

Concave, radiating pedal clavier
Organ bench with music shelf
Transparent music rack with light
Pedal light
Motor starter switch, key operated
DC current indicator light
Maas-Rowe control panel installation (panel by purchaser)